



EL3311 | 1-channel thermocouple input terminal with open-circuit recognition

The EL3311 analog input terminal allows thermocouples to be connected directly. The EtherCAT Terminal's circuit can operate thermocouple sensors using the 2-wire technique. Linearisation over the full temperature range is realised with the aid of a microprocessor. The temperature range can be selected freely. The error LEDs indicate a broken wire. Compensation for the cold junction is made through an internal temperature measurement at the terminal. The EL3311 can also be used for mV measurement.

| Technical data | EL3311 |
|------------------------------------|---|
| Number of inputs | 1 |
| Power supply | via the E-bus |
| Thermocouple sensor types | types K, J, L, E, T, N, U, B, R, S, C (default setting type K), mV measurement |
| Distributed clocks | – |
| Input filter limit frequency | typ. 1 kHz; dependent on sensor length, conversion time, sensor type |
| Connection method | 2-wire |
| Wiring fail indication | yes |
| Conversion time | approx. 750 ms up to 20 ms, depending on configuration and filter setting, default: approx. 75 ms |
| Temperature range | in the range defined in each case for the sensor (default setting: type K; $-200 \dots +1370$ °C); voltage measurement: ± 30 mV $\dots \pm 75$ mV |
| Resolution | 0.1 °C per digit |
| Measuring error | $< \pm 0.3$ % (relative to full scale value) |
| Electrical isolation | 500 V (E-bus/signal voltage) |
| Current consumption power contacts | – |
| Current consumption E-bus | 200 mA |
| Bit width in the process image | 1 x 32 bit TC input, 1 x 16 bit TC output |
| Special features | open-circuit recognition |
| Weight | approx. 60 g |
| Operating/storage temperature | $-25 \dots +60$ °C / $-40 \dots +85$ °C |
| Relative humidity | 95 %, no condensation |
| Vibration/shock resistance | conforms to EN 60068-2-6/EN 60068-2-27 |
| EMC immunity/emission | conforms to EN 61000-6-2/EN 61000-6-4 |
| Protect. class/installation pos. | IP 20/variable |
| Approvals | CE, UL, Ex |