

## Main

Range of product	Altivar 31
Product or component type	Variable speed drive
Product specific application	Simple machine Wire guiding
Component name	ATV31
Assembly style	Enclosed
EMC filter	Integrated
[Us] rated supply voltage	380...500 V - 15...10 %
Supply frequency	50...60 Hz - 5...5 %
Network number of phases	3 phases
Motor power kW	4 kW
Motor power hp	5 hp
Line current	10.6 A 500 V 1 kA 13.9 A 380 V 1 kA
Apparent power	9.2 kVA
Prospective line I <sub>sc</sub>	5 kA
Maximum transient current	14.3 A 60 s
Power dissipation in W	150 W at nominal load
Asynchronous motor control profile	Factory set : constant torque Sensorless flux vector control with PWM type motor control signal

## Complementary

Product destination	Asynchronous motors
Supply voltage limits	323...550 V
Network frequency limits	47.5...63 Hz
Speed drive output frequency	0.5...500 Hz
Nominal switching frequency	4 kHz
Switching frequency	2...16 kHz adjustable
Transient overtorque	150...170 % of nominal motor torque
Braking torque	30 % without braking resistor 100 % with braking resistor continuously ≤ 150 % with braking resistor 60 s
Regulation loop	Frequency PI regulator
Motor slip compensation	Adjustable Automatic whatever the load Suppressable
Output voltage	<= power supply voltage
Electrical connection	Terminal 2.5 mm <sup>2</sup> AWG 14 AI1, AI2, AI3, AOV, AOC, R1A, R1B, R1C, R2A, R2B, LI1...LI6 Terminal 2.5 mm <sup>2</sup> AWG 14 L1, L2, L3, U, V, W, PA, PB, PA/+, PC/-
Tightening torque	0.6 N.m AI1, AI2, AI3, AOV, AOC, R1A, R1B, R1C, R2A, R2B, LI1...LI6 0.8 N.m L1, L2, L3, U, V, W, PA, PB, PA/+, PC/-
Insulation	Electrical between power and control

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

Supply	Internal supply for logic inputs 19...30 V > 0...0.1 A short-circuit protection Internal supply for logic inputs 19...30 V > 0...0.1 A overload protection Internal supply for reference potentiometer 10...10.8 V > 0...0.01 A short-circuit protection Internal supply for reference potentiometer 10...10.8 V > 0...0.01 A overload protection
Analogue input number	3
Analogue input type	Configurable current AI3 0...20 mA 250 Ohm Configurable voltage AI1 0...10 V 30 V max 30000 Ohm Configurable voltage AI2 +/- 10 V 30 V max 30000 Ohm
Sampling duration	4 ms LI1...LI6 discrete 8 ms AI1, AI2, AI3 analog
Response time	8 ms discrete R1A, R1B, R1C, R2A, R2B 8 ms analog AOV, AOC
Linearity error	+/- 0.2 % output
Analogue output number	2
Analogue output type	Configurable current AOC 0...20 mA 800 Ohm 8 bits Configurable voltage AOV 0...10 V 470 Ohm 8 bits
Discrete input logic	Logic input not wired LI1...LI4 < 13 V Negative logic (source) LI1...LI6 > 19 V Positive logic (source) LI1...LI6 < 5 V > 11 V
Discrete output number	2
Discrete output type	Configurable relay logic R1A, R1B, R1C 1 NO + 1 NC 100000 cycles Configurable relay logic R2A, R2B NC 100000 cycles
Minimum switching current	10 mA 5 V DC R1-R2
Maximum switching current	2 A 250 V AC inductive cos phi = 0.4 L/R = 7 ms R1-R2 2 A 30 V DC inductive cos phi = 0.4 L/R = 7 ms R1-R2 5 A 250 V AC resistive cos phi = 1 L/R = 0 ms R1-R2 5 A 30 V DC resistive cos phi = 1 L/R = 0 ms R1-R2
Discrete input number	6
Discrete input type	Programmable LI1...LI6 24 V 0...100 mA PLC 3500 Ohm
Acceleration and deceleration ramps	S, U or customized Linear adjustable separately from 0.1 to 999.9 s
Braking to standstill	By DC injection
Protection type	Input phase breaks drive Line supply overvoltage and undervoltage safety circuits drive Line supply phase loss safety function, for three phases supply drive Motor phase breaks drive Overcurrent between output phases and earth (on power up only) drive Overheating protection drive Short-circuit between motor phases drive Thermal protection motor
Insulation resistance	≥ 500 MOhm 500 V DC for 1 minute
Time constant	5 ms for reference change
Frequency resolution	0.1...100 Hz analog input 0.1 Hz display unit
Type of connector	1 RJ45 Modbus 1 RJ45 CANopen via VW3 CANTAP2 adaptor
Physical interface	RS485 multidrop serial link Modbus
Transmission frame	RTU Modbus
Transmission rate	10, 20, 50, 125, 250, 500 kbps or 1 Mbps CANopen via VW3 CANTAP2 adaptor 4800, 9600 or 19200 bps Modbus
Number of addresses	1...127 CANopen via VW3 CANTAP2 adaptor 1...247 Modbus
Number of drive	31 Modbus 127 CANopen via VW3 CANTAP2 adaptor
Marking	CE
Operating position	Vertical +/- 10 degree
Product weight	10.7 kg

## Environment

Dielectric strength	2410 V DC between earth and power terminals 3400 V AC between control and power terminals
Electromagnetic compatibility	1.2/50 $\mu$ s - 8/20 $\mu$ s surge immunity test level 3 IEC 61000-4-5 Electrical fast transient/burst immunity test level 4 IEC 61000-4-4 Electrostatic discharge immunity test level 3 IEC 61000-4-2 Radiated radio-frequency electromagnetic field immunity test level 3 IEC 61000-4-3
Standards	EN 50178
Product certifications	C-Tick CSA N998 UL
IP degree of protection	IP55
Pollution degree	2
Protective treatment	TC
Vibration resistance	1 gn 13...150 Hz EN/IEC 60068-2-6 1.5 mm 3...13 Hz EN/IEC 60068-2-6
Shock resistance	15 gn 11 ms EN/IEC 60068-2-27
Relative humidity	5...95 % without condensation IEC 60068-2-3 5...95 % without dripping water IEC 60068-2-3
Ambient air temperature for storage	-25...70 °C
Ambient air temperature for operation	-10...50 °C without derating with protective cover on top of the drive -10...60 °C with derating factor without protective cover on top of the drive
Operating altitude	$\leq$ 1000 m without derating $\leq$ 1000 m without $\geq$ 1000 m with current derating 1 % per 100 m
RoHS EUR status	Will not be compliant