

## Power and error message module - TC-MACX-MCR-PTB - 2904673

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (<http://phoenixcontact.com/download>)



Power and fault signaling module with screw connection, only for use on the Termination Carrier, excluding corresponding DIN rail bus connector

### Your advantages

- ✓ Simple or redundant supply, decoupled from diode, protected against polarity reversal
- ✓ Installation in zone 2 permitted (protection type "n" according to EN 60079-15)
- ✓ Error message in the event of energy supply failure or fuse fault, can be selected and deselected via DIP switch
- ✓ Bus cable error message for MACX MCR-...(2)NAM... devices connected via DIN rail connectors, can be selected and deselected via DIP switch
- ✓ Relay output (changeover contact) and blinking LED for error messages
- ✓ Supply current up to 2 A (max. 2 x 2,5 AT backup fuse required)
- ✓ May only be used on the Termination Carrier
- ✓ Undervoltage detection at the input, can be selected and deselected via DIP switch (set to 19.2 V supply voltage)



### Key Commercial Data

Packing unit	1 pc
GTIN	 4 046356 892407
GTIN	4046356892407
Custom tariff number	90303370
Country of origin	Germany