

# BRH0854P22A1A

AC servo motors BRH - 4.8 N.m - 6000 rpm -  
untapped shaft - without brake - IP56

## Main

Product or component type	Motion servo motors
Component name	BRH
Continuous stall torque	4.8 N.m
Peak stall torque	9.3 N.m for LXM05AD22N4 9.3 N.m for LXM05BD22N4 9.3 N.m for LXM05CD22N4 13 N.m for LXM05AD28F1 13 N.m for LXM05AD28M2 13 N.m for LXM05BD28F1 13 N.m for LXM05BD28M2 13 N.m for LXM05CD28F1 13 N.m for LXM05CD28M2 18.3 N.m for LXM05AD42M3X 18.3 N.m for LXM05BD42M3X 18.3 N.m for LXM05CD42M3X
Nominal output power	740 W for LXM05BD28F1 740 W for LXM05CD28F1 740 W for LXM05AD28F1 1250 W for LXM05BD28M2 1250 W for LXM05CD28M2 1250 W for LXM05AD28M2 1400 W for LXM05BD22N4 1400 W for LXM05CD22N4 1400 W for LXM05AD22N4 1450 W for LXM05BD42M3X 1450 W for LXM05CD42M3X 1450 W for LXM05AD42M3X
Nominal speed	1500 rpm for LXM05AD28F1 1500 rpm for LXM05BD28F1 1500 rpm for LXM05CD28F1 3000 rpm for LXM05AD28M2 3000 rpm for LXM05BD28M2 3000 rpm for LXM05CD28M2 4000 rpm for LXM05AD42M3X 4000 rpm for LXM05BD42M3X 4000 rpm for LXM05CD42M3X 6000 rpm for LXM05AD22N4 6000 rpm for LXM05BD22N4 6000 rpm for LXM05CD22N4
Maximum mechanical speed	6000 rpm
Product compatibility	LXM05AD22N4 at 400/480 V 3 phases LXM05AD28F1 at 115 V single phase LXM05AD28M2 at 230 V single phase LXM05AD42M3X at 230 V 3 phases LXM05BD22N4 at 400/480 V 3 phases LXM05BD28F1 at 115 V single phase LXM05BD28M2 at 230 V single phase LXM05BD42M3X at 230 V 3 phases LXM05CD22N4 at 400/480 V 3 phases LXM05CD28F1 at 115 V single phase LXM05CD28M2 at 230 V single phase LXM05CD42M3X at 230 V 3 phases
Shaft end	Untapped
IP degree of protection	IP56
Encoder type	Multiturn SinCos Hiperface
Encoder feedback resolution	131072 points/turn x 4096 turns
Holding brake	Without
Mounting support	International standard flange

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

Electrical connection	Straight connectors
Number of poles	10

## Complementary

Range compatibility	Lexium 05
Switching frequency	8 kHz
Nominal torque	4 N.m for LXM05AD28M2 4 N.m for LXM05AD42M3X 4 N.m for LXM05BD28M2 4 N.m for LXM05BD42M3X 4 N.m for LXM05CD28M2 4 N.m for LXM05CD42M3X 4.71 N.m for LXM05AD28F1 4.71 N.m for LXM05BD28F1 4.71 N.m for LXM05CD28F1 9.3 N.m for LXM05AD22N4 9.3 N.m for LXM05BD22N4 9.3 N.m for LXM05CD22N4
Maximum current I <sub>rms</sub>	14 A for LXM05AD22N4 14 A for LXM05BD22N4 14 A for LXM05CD22N4 20 A for LXM05AD28F1 20 A for LXM05AD28M2 20 A for LXM05BD28F1 20 A for LXM05BD28M2 20 A for LXM05CD28F1 20 A for LXM05CD28M2 30 A for LXM05AD42M3X 30 A for LXM05BD42M3X 30 A for LXM05CD42M3X
Torque constant	0.68 N.m/A rms at 120 °C
Back emf constant	44 V rms/krpm at 120 °C
Rotor inertia	3.9 kg.cm <sup>2</sup> without brake 4.44 kg.cm <sup>2</sup> with brake
Stator resistance	0.9 Ohm
Stator inductance	3.6 mH
Stator electrical time constant	4.2 ms
Maximum radial force Fr	230 N at 6000 rpm 234 N at 5000 rpm 241 N at 4000 rpm 248 N at 3000 rpm 256 N at 2000 rpm 300 N at 1000 rpm
Maximum axial force Fa	0.2 x Fr
Product weight	6.1 kg

## Environment

RoHS EUR conformity date	4Q2009
RoHS EUR status	Will be compliant