

Withdrawable circuit breaker with guide frame, IEC 60947-2, frame size 1, 3-poles,  $I_n=1600\text{A}$  up to 690V AC 50/60Hz, breaking capacity  $N I_{cu}=55/42\text{kA}$  at 500/690V, Trip unit ETU600 LSIG upgrade ready, color display, bluetooth and USB interface, Protection LT, ST, INST, GFx, N-protection required an external N-sensor, incl. trip alarm switch (1xCO), rear connection horizontal, guide frame with shutter and position signal. switch (3xW), without Com & metering function Manual operating mechanism with mechanical closing, without Spring charging motor, Ready-to-close signal. switch, Auxiliary switches 2NO+2NC, without Closing coil (CC), manual operating mechanism with mechanical closing, without Remote trip alarm reset coil (RR), without 2nd shunt trip, without 1st Shunt trip

Model	
product brand name	SENTRON
product designation	3WA air circuit breaker
suitability for use	circuit breaker
size of the circuit-breaker	I
number of poles	3
position / of neutral conductor	no internal N-conductor
fastening method	withdrawable circuit breaker
design of the product	AC application
type of the driving mechanism	manual operating mechanism with mechanical or electrical closing
design of the electronic trip unit	ETU600 LSIG
Weight	76.937 kg
Net Weight	61.937 kg
General technical data	
insulation voltage / rated value	1000 V
operating voltage / at AC / at 50/60 Hz / rated value	690 V
power loss [W] / maximum	310 W
Current	
continuous current / rated value / maximum	1600 A
continuous current / rated value	1600 A
operational current	
• at 40 °C / rated value	1600 A
• at 45 °C / rated value	1600 A
• at 50 °C / rated value	1600 A
• at 55 °C / rated value	1600 A
• at 60 °C / rated value	1600 A
• at 70 °C / rated value	1490 A
Switching capacity and short-time withstand current, according to IEC 60947-2	
switching capacity class of the circuit breaker	N
maximum short-circuit current breaking capacity ( $I_{cu}$ )	
• at 500 V / rated value	55 kA
• at 690 V / rated value	42 kA
operating short-circuit current breaking capacity ( $I_{cs}$ )	
• at 500 V / rated value	55 kA
• at 690 V / rated value	42 kA
short-circuit current making capacity ( $I_{cm}$ )	
• at 500 V / rated value	121 kA
• at 690 V / rated value	88 kA
short-time withstand current ( $I_{cw}$ ) / at 500 V AC	
• for 0.5 s / rated value	55 kA

<ul style="list-style-type: none"> <li>• for 1 s / rated value</li> <li>• for 2 s / rated value</li> <li>• for 3 s / rated value</li> </ul>	50 kA 45 kA 35 kA
short-time withstand current (I <sub>cw</sub> ) / at 690 V AC	
<ul style="list-style-type: none"> <li>• for 0.5 s / rated value</li> <li>• for 1 s / rated value</li> <li>• for 2 s / rated value</li> <li>• for 3 s / rated value</li> </ul>	42 kA 42 kA 42 kA 35 kA














#### Electronic release unit

product feature	
<ul style="list-style-type: none"> <li>• upgradable</li> <li>• Bluetooth and USB interface</li> <li>• decoder for basic protection functions</li> <li>• display and function keys</li> <li>• SENTRON powerconfig configuration software</li> </ul>	Yes Yes Yes Yes Yes

#### Basic protection functions

product feature / for L-tripping	
<ul style="list-style-type: none"> <li>• can be switched on/off</li> <li>• selectable characteristic function</li> <li>• decoder and infinite adjustability are selectable with eSet</li> </ul>	Yes Yes Yes
set values setting current (I <sub>r</sub> ) / for L-tripping / with I2t characteristic	0.5;0.6;0.7;0.75;0.8;0.85;0.9;0.95;1.0
reference value setting current (I <sub>r</sub> ) / for L-tripping / with I2t characteristic	x I <sub>n</sub>
set values delay time (t <sub>r</sub> ) / for L-tripping / with I2t characteristic	1;2;5;8;10;14;17;21;25
reference value delay time (t <sub>r</sub> ) / for L-tripping / with I2t characteristic	s
set values setting current (I <sub>r</sub> ) / for L-tripping / with I2t characteristic / for eSet	0.4-1;0.001
adjustable absolute value setting current (I <sub>r</sub> ) / for L-tripping / with I2t characteristic / for eSet	
<ul style="list-style-type: none"> <li>• minimum</li> <li>• maximum</li> </ul>	640 A 1600 A
set values delay time (t <sub>r</sub> ) / for L-tripping / with I2t characteristic / for eSet	0.5-30;0.001
set values setting current (I <sub>r</sub> ) / for L-tripping / with I4t characteristic / for eSet	0.4-1;0.001
set values delay time (t <sub>r</sub> ) / for L-tripping / with I4t characteristic / for eSet	0.5-5;0.001
reference value delay time (t <sub>r</sub> ) / for L-tripping / with I4t characteristic	s
adjustable absolute value setting current (I <sub>r</sub> ) / for L-tripping / with I4t characteristic / for eSet	
<ul style="list-style-type: none"> <li>• minimum</li> <li>• maximum</li> </ul>	640 A 1600 A
<b>L: Overload protection N-conductor</b>	
product feature / with neutral conductor protection / can be switched on/off	Yes
setting values setting current (I <sub>nN</sub> ) / for N-tripping	0.2-2;0.001
reference value setting current (I <sub>nN</sub> ) / for N-tripping	x I <sub>n</sub>
adjustable setting current (I <sub>nN</sub> ) / for N-tripping	
<ul style="list-style-type: none"> <li>• minimum</li> <li>• maximum</li> </ul>	320 A 3200 A
<b>S: delayed short-circuit protection ST</b>	
product feature / for S-tripping	
<ul style="list-style-type: none"> <li>• independent of direction / can be switched on/off</li> <li>• independent of direction / selectable characteristic function</li> <li>• decoder and infinite adjustability are selectable with eSet</li> </ul>	Yes Yes Yes
<b>S: delayed short-circuit protection ST, settings values I0t</b>	
set values setting current (I <sub>sd</sub> ) / for S-tripping / with I0t characteristic	1.5;2;2.5;3;4;5;6;8;10
reference value setting current (I <sub>sd</sub> ) / for S-tripping / with I0t characteristic	x I <sub>r</sub>
set values delay time (t <sub>sd</sub> ) / for S-tripping / with I0t characteristic	0.08;0.15;0.22;0.3;0.4

reference value delay time (tsd) / for S-tripping / with I0t characteristic	s
set values setting current (Isd) / for S-tripping / with I0t characteristic / for eSet / independent of direction	0.6-10;0.001
adjustable absolute value setting current (Isd) <ul style="list-style-type: none"> <li>• for S-tripping / with I0t characteristic / for eSet / independent of direction / minimum</li> <li>• at 500 V / for S-tripping / with I0t characteristic / for eSet / independent of direction / maximum</li> <li>• at 690 V / for S-tripping / with I0t characteristic / for eSet / independent of direction / maximum</li> </ul>	960 A 40 kA 33.6 kA
set values delay time (tsd) / for S-tripping / with I0t characteristic / for eSet / independent of direction	0.02-0.4;0.001
<b>S: delayed short-circuit protection ST, settings values I2t</b>	
set values setting current (Isd) / for S-tripping / with I2t characteristic	1.5;2;2.5;3;4;5;6;8;10
reference value setting current (Isd) / for S-tripping / with I2t characteristic	x Ir
set values delay time (tsd) / for S-tripping / with I2t characteristic	0.1;0.2;0.3;0.4
set values setting current (Isd) / for S-tripping / with I2t characteristic / for eSet / independent of direction	0.6-10;0.001
adjustable absolute value setting current (Isd) <ul style="list-style-type: none"> <li>• for S-tripping / with I2t characteristic / for eSet / independent of direction / minimum</li> <li>• at 500 V / for S-tripping / with I2t characteristic / for eSet / independent of direction / maximum</li> <li>• at 690 V / for S-tripping / with I2t characteristic / for eSet / independent of direction / maximum</li> </ul>	960 A 40 kA 33.6 kA
set values delay time (tsd) / for S-tripping / with I2t characteristic / for eSet / independent of direction	0.02-0.4;0.001
product feature / for I-tripping <ul style="list-style-type: none"> <li>• can be switched on/off</li> <li>• decoder and infinite adjustability are selectable (with eSet)</li> </ul>	Yes Yes
set values setting current (Ii) / for I-tripping	1.5;2;3;4;6;8;10;12;15
reference value setting current (Ii) / for I-tripping	x In
tripping factor setting current (Iimax) / for I-tripping	0.8
reference value setting current (Iimax) / for I-tripping	x Ics
set values setting current (Ii) / for I-tripping / for eSet	1.5-15;0.001
adjustable absolute value setting current (Ii) <ul style="list-style-type: none"> <li>• for I-tripping / for eSet / minimum</li> <li>• at 500 V / for I-tripping / for eSet / maximum</li> <li>• at 690 V / for I-tripping / for eSet / maximum</li> </ul>	2400 A 44 kA 33.6 kA
<b>G: ground fault GF</b>	
product feature / for G-tripping <ul style="list-style-type: none"> <li>• can be switched on/off</li> <li>• selectable characteristic function</li> </ul>	Yes Yes
set values setting current (Ilg) / for G-tripping / with I0t characteristic	0.0625-1.25;0.001
reference value setting current (Ilg) / for G-tripping / with I0t characteristic	x In
set values delay time (tgg) / for G-tripping / with I0t characteristic	0.02-30;0.001
reference value delay time (tgg) / for G-tripping / with I0t characteristic	s
set values setting current (Ilg) / for G-tripping / with I2t characteristic	0.0625-1.25;0.001
reference value setting current (Ilg) / for G-tripping / with I2t characteristic	x In
set values delay time (tgg) / for G-tripping / with I2t characteristic	0.02-5;0.001
reference value delay time (tgg) / for G-tripping / with I2t characteristic	s
<b>Further protective functions</b>	
protection function <ul style="list-style-type: none"> <li>• maintenance mode DAS+</li> </ul>	Yes
<b>Measuring functions</b>	
measurement function <ul style="list-style-type: none"> <li>• current measurement</li> </ul>	Yes

Communication					
communication function	No				
Service Life					
mechanical service life (operating cycles)					
• without support / typical	15000				
• with support / typical	30000				
electrical endurance (operating cycles)					
• at 690 V / without support / typical	10000				
• at 690 V / with support / typical	30000				
Dimensions					
height	468 mm				
width	320 mm				
depth	471 mm				
Main connection					
arrangement of electrical connectors / for main current circuit	main connection on the rear, horizontal				
Auxiliary circuit					
design of the auxiliary switch	2 NO + 2 NC				
number of NC contacts / for auxiliary contacts	2				
number of NO contacts / for auxiliary contacts	2				
number of CO contacts / for auxiliary contacts	0				
Internal accessories					
product component					
• undervoltage release	No				
• voltage trigger	No				
• trip indicator	Yes				
• motor drive	No				
Environmental conditions					
protection class IP / on the front	IP20				
ambient temperature / during operation					
• minimum	-40 °C				
• maximum	70 °C				
ambient temperature / during storage					
• minimum	-40 °C				
• maximum	80 °C				
Certificates					
reference code					
• according to IEC 81346-2	Q				
General Product Approval					
     					
EMV					
Radio Equipment Type Approval Certificate			Test Certificates		
<a href="#">Miscellaneous</a> 			<a href="#">Miscellaneous</a> 		
<a href="#">Special Test Certificate</a>			<a href="#">Miscellaneous</a>		
Maritime application					other
    					<a href="#">Manufacturer Declaration</a>
other		Dangerous goods		Environment	



[Confirmation](#)

[Transport Information](#)

[Dangerous goods information](#)



## Environment



## Further information

Information on the packaging

<https://support.industry.siemens.com/cs/ww/en/view/109813875>

Industry Mall (Online ordering system)

<https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3WA1116-2AF62-0AA0>

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

<https://support.industry.siemens.com/cs/ww/en/ps/3WA1116-2AF62-0AA0>

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)

[http://www.automation.siemens.com/bilddb/cax\\_en.aspx?mlfb=3WA1116-2AF62-0AA0](http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3WA1116-2AF62-0AA0)

CAX-Online-Generator

<http://www.siemens.com/cax>

Information- and Downloadcenter (catalogues, leaflets,...)

<http://www.siemens.com/energy-automation>

