



 PRODUCT-DETAILS

MS325-4-HKF11

MS325-4-HKF11 Manual Motor Starter 2.5 ... 4.0 A

For sale but "Obsolete", replaced by



General Information

Extended Product Type	MS325-4-HKF11
Product ID	1SAM150005R0008
EAN	4013614302466
Catalog Description	MS325-4-HKF11 Manual Motor Starter 2.5 ... 4.0 A

Long Description	<p>The MS325-4-HKF11 manual motor starter is a 54 mm width devices with a rated operational current of $I_e = 4.0$ A and a pre-assembled front mounted auxiliary contact HKF1-11. This device is used to manually switch on and off motors and to protect them reliably and without the need for a fuse from short-circuits, overload and phase failures. The manual motor starter offers a rated service short-circuit breaking capacity $I_{cs} = 100$ kA at 400 VAC and the trip class 10A. Further features are the build-in disconnect function, temperature compensation, trip-free mechanism and a rotary handle with a clear switch position indication. The manual motor starter is suitable for three- and single-phase applications. Auxiliary contacts, signalling contacts, undervoltage releases, shunt trips, 3-phase bus bars, power in-feed blocks and locking devices for protection against unauthorized changes are available as accessory.</p>
------------------	---

Ordering

Minimum Order Quantity	1 piece
Customs Tariff Number	85362010

Replacement Product ID
(NEW)

1SAM350005R1008

Popular Downloads

Data Sheet, Technical Information	2CDC131046D0201
Instructions and Manuals	2CDC131089M6801
Time-Current Characteristic Curve	1SAM100513F0008

Dimensions

Product Net Width	54 mm
Product Net Height	87.5 mm
Product Net Depth / Length	75.5 mm
Product Net Weight	0.36 kg

Technical

Rated Service Short-Circuit Breaking Capacity (I_{cs})	(230 V AC) 100 kA (400 V AC) 100 kA (440 V AC) 100 kA (500 V AC) 60 kA (690 V AC) 10 kA
Rated Ultimate Short-Circuit Breaking Capacity (I_{cu})	(230 V AC) 100 kA (400 V AC) 100 kA (440 V AC) 100 kA (500 V AC) 60 kA (690 V AC) 10 kA
Rated Instantaneous Short-Circuit Current Setting (I_i)	50 A
Setting Range	2.5 ... 4.0 A
Rated Operational Power AC-3 (P_e)	(400 V) Three Phase 1.5 kW
Rated Operational Voltage	Main Circuit 690 V AC Main Circuit 440 V DC Main Circuit 690 V AC Main Circuit 440 V DC
Rated Operational Current (I_e)	4 A
Rated Operational Current AC-3 (I_e)	4 A
Rated Frequency (f)	Main Circuit 60 Hz Main Circuit 50 Hz Main Circuit 50 Hz Main Circuit 60 Hz
Rated Impulse Withstand Voltage (U_{imp})	Main Circuit 6 kV
Rated Insulation Voltage (U_i)	690 V
Power Loss	at Rated Operating Conditions per Pole 0.9 ... 2.3 W
Number of Poles	3P
Mounted Auxiliary Contacts	1 NO, 1 NC

Number of Auxiliary Contacts NC	1
Number of Auxiliary Contacts NO	1
Conventional Free-air Thermal Current (I _{th})	Main Circuit 4 A
Degree of Protection	Housing IP20 Main Circuit Terminals IP20
Pollution Degree	3
Electrical Durability	50000 cycle
Mechanical Durability	Nr. Operations 100000 cycle
Terminal Type	Screw Terminals
Connecting Capacity Main Circuit	Flexible with Ferrule 1/2x 0.75 ... 4 mm ² Flexible with Insulated Ferrule 1/2x 0.75 ... 4 mm ² Flexible 1/2x 1 ... 6 mm ² Rigid 1/2x 1 ... 6 mm ²
Tightening Torque	Main Circuit 1.4 N·m
Wire Stripping Length	Auxiliary Circuit 8 mm Main Circuit 10 mm
Recommended Screw Driver	Pozidriv 2 M3.5
Mounting Position	1 ... 6
Mounting on DIN Rail	TH35-15 (35 x 15 mm Mounting Rail) acc. to IEC 60715 TH35-7.5 (35 x 7.5 mm Mounting Rail) acc. to IEC 60715
Actuator Type	Rotary Handle
Contact Position Indication	ON / OFF
Standards	CSA 22.2 No. 14 IEC/EN 60947-1 IEC/EN 60947-2 IEC/EN 60947-4-1 IEC/EN 60947-5-1 UL 508

Technical UL/CSA

Maximum Operating Voltage UL/CSA	Main Circuit 600 V AC
Horsepower Rating UL/CSA	(220 ... 240 V AC) Three Phase 1 Hp (440 ... 480 V AC) Three Phase 2 Hp (550 ... 600 V AC) Three Phase 3 Hp
Connecting Capacity Main Circuit UL/CSA	Flexible 1/2x 14-8 AWG Stranded 1/2x 14-8 AWG
Tightening Torque UL/CSA	Auxiliary Circuit 7 in·lb Main Circuit 14 in·lb

Environmental

Ambient Air Temperature	Around the Enclosure 0 ... +40 °C Operation -25 ... +50 °C Operation Compensated -25 ... +50 °C Storage -50 ... +80 °C
Ambient Air Temperature Compensation	Yes
Maximum Operating Altitude Permissible	2000 m
Resistance to Shock acc. to IEC 60068-2-27	11 ms Pulse 15g
Resistance to Vibrations	5g 10 ... 150 Hz

Material Compliance

Conflict Minerals Reporting Template (CMRT)	9AKK108467A5658
REACH Declaration	1SAA960005-4502
RoHS Declaration	1SAA963006-4502
RoHS Information	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019
Toxic Substances Control Act - TSCA	2CMT2023-006539
WEEE B2C / B2B	Business To Business
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)

Certificates and Declarations

ATEX Certificate	1SAA918000-3903
BV Certificate	1SAA918000-0204
CB Certificate	1SAA918000-2002
CQC Certificate	CQC2017010307033534
cUL Certificate	cUL_E137861 cUL_E345003
Declaration of Conformity - CCC	2020980307003580
Declaration of Conformity - CE	1SAD101100-3412
Declaration of Conformity - UKCA	1SAD201100-3412
DNV Certificate	1SAA918000-0306
GL Certificate	1SAA918000-0403
LR Certificate	1SAA918000-0503
RINA Certificate	1SAA918000-0804
RMRS Certificate	1SAA918000-0704
UL Certificate	UL_E137861 UL_E345003

Container Information

Package Level 1 Units	box 1 piece
Package Level 1 Width	92 mm
Package Level 1 Depth / Length	58 mm
Package Level 1 Height	78 mm
Package Level 1 Gross Weight	0.39 kg
Package Level 1 EAN	4013614302466
Package Level 2 Units	carton 24 piece
Package Level 2 Width	280 mm
Package Level 2 Depth / Length	395 mm
Package Level 2 Height	210 mm
Package Level 2 Gross Weight	9.38 kg
Package Level 2 EAN	4013614494741

External Classifications and Standards

Object Classification Code	F
ETIM 9	EC000074 - Motor protection circuit-breaker
ETIM 10	EC000074 - Motor protection circuit-breaker
eClass	V11.0 : 27370401
UNSPSC	39121521
IDEA Granular Category Code (IGCC)	4845 >> 3 Pole Motor Circuit Protector Circuit Breakers

Categories

Low Voltage Products and Systems → Circuit Breakers → Manual Motor Starters

Low Voltage Products and Systems → Control Products → Manual Motor Starters → Manual Motor Starters

