




V430-F000M03M-SRX

V430 Code Reader, 0.3 MP Monochrome, Medium view, Autofocus 50-300 mm, Red light, X-Mode, Ethernet TCP/IP, EtherNet/IP, PROFINET, IP65/IP67

Specifications












| | |
|---------------------------|--|
| Number of pixels | 0.3 MP |
| Camera type | Monochrome |
| Autofocus | ✓ |
| Focus distance | 50-300 mm |
| Field of view (width) | 34-183 mm |
| Decoder type | X-Mode (advanced 1D+2D+DPM) |
| Frame rate | 60 fps |
| Illumination | Red LED |
| Image width | 752 pixels |
| Image height | 480 pixels |
| Shutter type | Global |
| Communication port(s) | EtherNet/IP, Ethernet TCP/IP, PROFINET Slave, Serial RS-232C |
| Digital output type | PNP |
| Product Height (unpacked) | 25.4 mm |
| Product Width (unpacked) | 44.5 mm |
| Product Depth (unpacked) | 56.9 mm |
| Product Weight (unpacked) | 68 g |
| Degree of protection (IP) | IP65/IP67 |

Accessories



98-9000045-03

V/F 4x0-F Red high brightness standard LED installation kit

| | | |
|--|------------------|--|
|  | V430-AF11 | Diffuser Installation Kit for V/F4X0-FXXXXXXXX-XXX |
|  | V430-AF12 | Polarizer Installation Kit for V/F4X0-FXXXXXXXX-XXX |
|  | V430-AF3 | V/F 4x0-F Right angle mirror |
|  | V430-AF4 | Kit, YAG Filter, F/V43XX |
|  | V430-AF5 | Kit, ESD Window, F/V4XX |
|  | V430-AF6 | V/F 4x0-F Standard Red filter Installation Kit |
|  | V430-AF7 | V/F 4x0-F Standard Blue filter Installation Kit |
|  | V430-AM0 | V/F 4x0-F L Bracket Adjustable Angle Mounting Kit |
|  | V430-AM1 | V/F 4x0-F 1/4-20 Camera Tripod Mounting Block Kit |
|  | V430-AM2 | V/F 4x0-F 4" (102 mm) Ram Mount Stand |
|  | V430-AM3 | V/F 4x0-F APG Pan and Tilt Camera Mount |
| | V430-AM4 | V/F 4x0-F Nylon Screw and Washer Electrical Isolation Mounting Kit |
| | V430-AM6 | V/F 4x0-F Smart Ring Light to V/F4XX-F Mounting Bracket |
| | V430-AM7 | V/F 4x0-F QX / Vision HAWK to V/F4XX-F Adapter Plate |



V430-W8-10M-E

V/F 430-F M12 to Flying Leads Cable, 10 m



V430-W8-15M-E

V/F 430-F M12 to flying leads cable, 15 m



V430-W8-20M-E

V/F 430-F M12 to Flying Leads Cable, 20 m



V430-W8-2M-E

V/F 430-F M12 to flying leads cable, 2 m



V430-W8-3M

V/F 430-F M12 to Flying Leads Cable, 3 m



V430-W8-5M

V/F 430-F M12 to Flying Leads Cable, 5 m



V430-W8F-3M

V/F 430-F M12 to Flying Leads Cable, with power filter, 3 m



V430-W8F-5M

V/F 430-F M12 to Flying Leads Cable, with power filter, 5 m

V430-W8LD-10M-E

V/F 430-F M12 to flying leads cable, right angle down, 10 m

V430-W8LD-15M-E

V/F 430-F M12 to flying leads cable, right angle down, 15 m

V430-W8LD-20M-E

V/F 430-F M12 to flying leads cable, right angle down, 20 m



V430-W8LD-3M








V/F 430-F M12 to Flying Leads Cable, right angle down, 3 m





V430-W8LD-5M-E

V/F 430-F M12 to flying leads cable, right angle down, 5 m

V430-W8LU-10M-E

V/F 430-F M12 to flying leads cable, right angle up, 10 m

| | | |
|--|------------------------|---|
| | V430-W8LU-15M-E | V/F 430-F M12 to flying feads cable, right angle up, 15 m |
| | V430-W8LU-20M-E | V/F 430-F M12 to flying leads cable, right angle up, 20 m |
| | V430-W8LU-3M | V/F 430-F M12 to Flying Leads Cable, right angle up, 3 m |
| | V430-W8LU-5M-E | V/F 430-F M12 to flying leads cable, right angle up, 5 m |
|  | V430-WE-10M-E | V/F 430-F Ethernet cable M12 plug on camera to RJ45 connector, 10 m |
|  | V430-WE-15M-E | V/F 430-F Ethernet cable M12 plug on camera to RJ45 connector, 15 m |
|  | V430-WE-1M | V/F 430-F Ethernet cable M12 plug on camera to RJ45 connector, 1 m |
|  | V430-WE-20M-E | V/F 430-F Ethernet cable M12 plug on camera to RJ45 connector, 20 m |
|  | V430-WE-2M-E | V/F 430-F Ethernet cable M12 plug on camera to RJ45 connector, 2 m |
|  | V430-WE-3M | V/F 430-F Ethernet cable M12 plug on camera to RJ45 connector, 3 m |
|  | V430-WE-5M | V/F 430-F Ethernet cable M12 plug on camera to RJ45 connector, 5 m |
| | V430-WELD-10M-E | V/F 430-F Ethernet cable M12 plug on camera to RJ45 connector, right angle down, 10 m |
| | V430-WELD-15M-E | V/F 430-F Ethernet cable M12 plug on camera to RJ45 connector, right angle down, 15 m |
| | V430-WELD-1M-E | V/F 430-F Ethernet cable M12 plug on camera to RJ45 connector, right angle down, 1 m |


| | | |
|---|------------------------|---|
| | V430-WELD-20M-E | V/F 430-F Ethernet cable M12 plug on camera to RJ45 connector, right angle down, 20 m |
| | V430-WELD-3M | V/F 430-F Ethernet cable M12 plug on camera to RJ45 connector, Right angle down, 3 m |
| | V430-WELD-5M-E | V/F 430-F Ethernet cable M12 plug on camera to RJ45 connector, right angle down, 5 m |
| | V430-WELU-10M-E | V/F 430-F Ethernet cable M12 plug on camera to RJ45 connector, Right angle up, 10 m |
| | V430-WELU-15M-E | V/F 430-F Ethernet cable M12 plug on camera to RJ45 connector, right angle up, 15 m |
| | V430-WELU-1M-E | V/F 430-F Ethernet cable M12 plug on camera to RJ45 connector, right angle up, 1 m |
| | V430-WELU-20M-E | V/F 430-F Ethernet cable M12 plug on camera to RJ45 connector, Right angle up, 20 m |
|  | V430-WELU-3M | V/F 430-F Ethernet cable M12 plug on camera to RJ45 connector, Right angle up, 3 m |
| | V430-WELU-5M-E | V/F 430-F Ethernet cable M12 plug on camera to RJ45 connector, right angle up, 5 m |
| | V430-WQ-1M | V/F 430-F Camera to QX-1 interconnect cable, M12 socket to M12 plug, 1 m |
| | V430-WQK-3M | V/F 430-F Camera to QX-1 interconnect cable with USB keyboard wedge breakout, 2.7 m |
|  | V430-WQR-3M | V/F 430-F Camera to QX-1 interconnect cable with RS-232 breakout, 2.7 m |
|  | V430-WR-1M | V/F 430-F Cable, M12 socket to RS-232 DB9 socket, 1 m |
|  | V430-WR-3M | V/F 430-F Cable, M12 socket to RS-232 DB9 socket, 3 m |



V430-AF10

Front Window Installation Kit for V/F4X0-FXXXXXXXX-XXX

CAD Library



Code Reader Technical Manual

EN PDF 1.08 MB



Code Reader Group Catalog

EN PDF 5.63 MB



EAC Mark removal Discontinuation Notice

EN PDF 221 KB



Firmware v2.2.0 Software

EN ZIP 35.9 MB



MicroHAWK Optics and Lighting Accessory Kit Installation Manual

EN PDF 8.25 MB



MicroHAWK V Series Users Manual

EN PDF 47.9 MB



MicroHAWK V Series Brochure

EN PDF 1.58 MB



MicroHAWK V Series Communications Manual

EN PDF 6.7 MB



MicroHAWK V430-F Datasheet

EN PDF 8.14 MB



NX-series -[Ethernet TCP/IP]- V330-F, V430-F Code Readers Connection Guide

EN PDF 2.89 MB



NX-series -[RS-232C]- V320-F, V420-F, V430-F Code Readers Connection Guide

EN PDF 2.48 MB



OMRON_Microscan_DDU_Installer_4.0.0 Software

EN ZIP 40.3 MB



Omron V430-F, V330-F EtherNet/IP EDS file

EN ZIP 389 KB



Omron V430-F, V330-F PROFINET GSDML file

EN ZIP 353 KB



Traceability Solutions Toolbox Software

EN ZIP 6.05 MB



V420-F/V430-F MicroHAWK Autofocus Multi Code Reader Brochure

EN PDF 4.77 MB



V430-F Leaflet

EN PDF 1.11 MB

