


# Product datasheet

Specifications



## Remote Control Electrical Motor 200 to 250 VDC

EXECH20D

EAN Code: 3606480988318

### Main

Range of product	EasyPact EXE Evolis
Device short name	MCH
Product or component type	Motor mechanism
Range compatibility	Evolis EasyPact EXE
Device application	Automatic spring charging

### Complementary

Control type	Remote control
Rated supply voltage of auxiliary and control circuits (Ua)	200...250 V DC
Threshold tripping voltage	0.85...1.1 Ua
Charging time	6 s maximum
Maximum operating frequency	<= 3 cycles per minute
Overcurrent protection	2...3 x I <sub>n</sub> 0.1 s motor
Power consumption in W	180 W
Input current	10 mA at 240 V
Mounting mode	Fixed
Accessory / separate part category	Spare part
Accessory / separate part type	Base function

### Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	12.6 cm
Package 1 Width	13.3 cm
Package 1 Length	22.9 cm
Package 1 Weight	1.893 kg
Unit Type of Package 2	S03
Number of Units in Package 2	6
Package 2 Height	30.0 cm
Package 2 Width	30.0 cm
Package 2 Length	40.0 cm

---

Package 2 Weight 11.9 kg

## Logistical informations

---

Country of origin FR

## Contractual warranty

---

Warranty (in months) 18



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better



#### Materials and Substances

Packaging made with recycled cardboard	No
Packaging without single use plastic	No
SCIP Number	409e50bf-7b4e-47fe-83a3-6420f9386633
EU RoHS Directive	<a href="#">Compliant By Exemption</a>
REACH Regulation	<a href="#">Reference contains Substances of Very High Concern above the threshold</a>
PVC free	No

### Use Longer



#### Lifetime extension

Repair	No
--------	----

### Use Again



#### Repack and remanufacture

End of life manual availability	<a href="#">End of Life Information</a>
Take-back	Nej