



EL2622-0010 | 2-channel relay output terminal 230 V AC, 5 A, make contacts, no power contacts, contact-protecting switching of LED lamps

The EL2622-0010 output terminal has two relays each of which has a single contact. The relay terminal is designed for soft switching at the zero voltage crossing to protect the contacts and is particularly suitable for capacitive loads such as LED lamps. The power contacts are not looped through. The EtherCAT Terminal indicates its signal state by means of light emitting diodes.

Technical data	EL2622-0010 ES2622-0010
Connection technology	relay output
Number of outputs	2 x make contacts
Nominal voltage	230 V AC/30 V DC
Load type	ohmic, inductive, capacitive
Distributed clocks	–
Switching current	5 A AC/DC per channel
Inductive switching current	2 A AC/DC per channel
Minimum permitted load	0.1 mA at 0.1 V DC
Current consumption E-bus	typ. 120 mA
Electrical isolation	500 V (E-bus/field potential)
Current consumption power contacts	–
Bit width in the process image	2 outputs + 1 input
Operating cycles mech. (min.)	2 x 10 ⁷
Operating cycles electr. (min.)	8 x 10 ⁴ (5 A/30 V DC or 5 A/250 V AC and ohmic load)
Configuration	no address or configuration setting
Special features	soft switching at zero voltage crossing
Weight	approx. 50 g
Operating/storage temperature	0...+55 °C/-25...+85 °C
Relative humidity	95 %, no condensation
Vibration/shock resistance	conforms to EN 60068-2-6/EN 60068-2-27
EMC immunity/emission	conforms to EN 61000-6-2/EN 61000-6-4
Protect. class/installation pos.	IP 20/variable
Pluggable wiring	for all ESxxxx terminals
Approvals	CE

Related products	
EL2602-0010	2-channel relay output terminal 230 V AC, 5 A, make contacts, contact-protecting switching of LED lamps
KL2602-0010	2-channel relay output terminal 230 V AC, 5 A, make contacts, contact-protecting switching of LED lamps
KL2622-0010	2-channel relay output terminal, 230 V AC, 5 A, make contacts, no power contacts, contact-protecting switching of LED lamps