



Sensor output interface terminal KCD2-E1

- 1-channel terminal amplifier
- NAMUR sensor input
- DC 24 V supply voltage
- Standard interface for prevention of signal transmission errors
- Switching status indicator, yellow LED
- Short-circuit proof electronic output
- Low noise sensitivity
- Compact terminal housing
- Clips onto standard 35 mm rail to DIN EN 50 022
- Degree of protection IP20

Sensor output interface terminal



Technical Data

Functional safety related parameters		
MTTF _d		1612 a
Indicators/operating means		
LED yellow		switch output
Electrical specifications		
Operating voltage	U _B	10 ... 30 V DC
Ripple		≤ 10 %
Operating current	I _B	approx. 22 mA
Input		
Connection		terminals 1+, 2-
Connectable sensor types		NAMUR
Pulse length/pulse interval		≥ 0.5 ms / ≥ 0.5 ms
Short-circuit current		approx. 8 mA
Sensor supply		8 V DC
Switching point		1.2 ... 2.1 mA hysteresis approx. 0.2 mA
Line fault detection		without
Trip value		1 kHz
Output		
Connection		terminal 4-
Current		200 mA short-circuit protected
Transistor		NPN
Signal level		U _B - 1.8V
Transfer characteristics		
Mode of operation		NC contact
Switching frequency		1 kHz
Directive conformity		
Electromagnetic compatibility		
Directive 2014/30/EU		EN 61326-1:2013
Standard conformity		
Degree of protection		EN 60529:2000
Noise immunity		EN 61326-1:2013
Ambient conditions		
Ambient temperature		-25 ... 70 °C (-13 ... 158 °F)

Release date: 2020-03-24 Date of issue: 2020-03-26 Filename: 269795_eng.pdf

Refer to "General Notes Relating to Pepperl+Fuchs Product Information".

Pepperl+Fuchs Group
www.pepperl-fuchs.com

USA: +1 330 486 0001
fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 1111
fa-info@de.pepperl-fuchs.com

Singapore: +65 6779 9091
fa-info@sg.pepperl-fuchs.com

 PEPPERL+FUCHS

Technical Data

Storage temperature	-25 ... 85 °C (-13 ... 185 °F)
Mechanical specifications	
Connection	self-opening apparatus connection terminals, max. core cross-section 0.34 ... 2.5 mm ²
Mass	60 g
Dimensions	20x60x40 (in mm)