


# Inductive sensor BI5-Q08-VP6X2

**TURCK**

Industrial  
Automation



- Rectangular, height 8 mm
- Active face on top
- Metal, zinc die casting
- 4-wire DC, 10...30 VDC
- Changeover contact, PNP output
- Cable connection

### Wiring diagram



### Functional principle

Inductive sensors detect metal objects contactless and wear-free. For this, they use a high-frequency electromagnetic AC field that interacts with the target. Inductive sensors generate this field via an RLC circuit with a ferrite coil.

We offer special versions for temperatures of -60 °C up to +250 °C.

<b>Type code</b>	BI5-Q08-VP6X2
Ident no.	16001
<b>Rated operating distance Sn</b>	5 mm
Mounting condition	flush
Assured sensing range	$\leq (0,81 \times S_n)$ mm
Correction factors	St37 = 1; Al = 0.3; stainless steel = 0.7; Ms = 0.4
Repeatability	$\leq 2\%$ of full scale
Temperature drift	10 %
Hysteresis	3...15 %
Ambient temperature	-25...+70 °C
<b>Operating voltage</b>	10...30VDC
Residual ripple	$\leq 10\%$ U <sub>ss</sub>
DC rated operational current	$\leq 200$ mA
No-load current I <sub>0</sub>	$\leq 15$ mA
Residual current	$\leq 0.1$ mA
Rated insulation voltage	$\leq 0.5$ kV
Short-circuit protection	yes/ cyclic
Voltage drop at I <sub>e</sub>	$\leq 1.8$ V
Wire breakage / Reverse polarity protection	yes/ complete
Output function	4-wire, changover contact, PNP
Switching frequency	1 kHz
<b>Design</b>	rectangular, Q08
Dimensions	32 x 20 x 8 mm
Housing material	metal, GD-Zn
Connection	cable
Cable quality	4 mm, LiFY-11Y, PUR, 2 m
Cable cross section	4 x 0.25 mm <sup>2</sup>
Vibration resistance	55 Hz (1 mm)
Shock resistance	30 g (11 ms)
Protection class	IP67
MTTF	2283 years acc. to SN 29500 (Ed. 99) 40 °C
<b>Power-on indication</b>	LED green
Switching state	LED yellow

**Inductive sensor  
BI5-Q08-VP6X2**

---

Distance D	2 x B
Distance W	3 x Sn
Distance S	1 x B
Distance G	6 x Sn

---

Width of the active face B 20 mm

---

