



SIRIUS SAFETY RELAY WITH RELAY RELEASE CIRCUITS (RC),  
 UC 24...240V, 45.0MM, SCREW TERMINAL,  
 RC INSTANT.: 4NO, RC DELAYED: 0, MK: 2,  
 8-FUNCTION SWITCH, BASIC DEVICE,  
 MAX. ACHIEVABLE PL TO EN13849-1: E,  
 MAX. ACHIEVABLE SIL TO IEC61508:3,

General technical details:		
product brand name		SIRIUS
product designation		safety relays
Design of the product		for EMERGENCY-STOP units
protection class IP / of the housing		IP20
Protection class IP / of the terminal		IP20
Protection against electrical shock		finger-safe
Insulation voltage / rated value	V	300
Ambient temperature		
• during storage	°C	-40 ... +80
• during operating	°C	-25 ... +60
Air pressure		
• according to SN 31205	kPa	90 ... 106
Relative humidity		
• during operating phase	%	10 ... 95
Installation altitude / at a height over sea level / maximum	m	2,000
Resistance against vibration / according to IEC 60068-2-6		5 ... 500 Hz: 0,075 mm
Resistance against shock		8g / 10 ms
Impulse voltage resistance / rated value	V	4,000
EMC emitted interference		EN 60947-5-1

<b>Installation environment relating to EMC</b>		This product is suitable for Class A environments only. It can cause undesired radio-frequency interference in residential environments. If this is the case, the user must take appropriate measures.
<b>Item designation</b> <ul style="list-style-type: none"> <li>• according to DIN 40719 extendable after IEC 204-2 / according to IEC 750</li> <li>• according to DIN EN 61346-2</li> </ul>		KT  F
<b>Number of sensor inputs</b> <ul style="list-style-type: none"> <li>• 1-channel or 2-channel</li> </ul>		1
<b>Design of the cascading</b>		cascading or in-service switching
<b>Type of the safety-related wiring / of the inputs</b>		single-channel and two-channel
<b>Product feature / transverse contact-secure</b>		Yes
<b>Safety Integrity Level (SIL)</b> <ul style="list-style-type: none"> <li>• according to IEC 61508</li> </ul>		SIL3
<b>SIL claim limit (for a subsystem) / according to EN 62061</b>		3
<b>Performance Level (PL)</b> <ul style="list-style-type: none"> <li>• according to ISO 13849-1</li> </ul>		e
<b>Category / according to EN 954-1</b>		4
<b>Category / according to ISO 13849-1</b>		4
<b>Hardware fault tolerance / according to IEC 61508</b>		1
<b>Safety device type / according to IEC 61508-2</b>		Type B
<b>Probability of dangerous failure per hour (PFHD) / with high demand rate / according to EN 62061</b>	1/h	0.78E-8
<b>Average probability of failure on demand (PFDavg) / with low demand rate / according to IEC 61508</b>	1/y	0.15E-4
<b>T1 value / for proof test interval or service life / according to IEC 61508</b>	a	20
<b>Number of outputs / as contact-affected switching element</b> <ul style="list-style-type: none"> <li>• as NC contact / for reporting function / instantaneous switching</li> <li>• as NO contact / safety-related / instantaneous switching</li> <li>• as NO contact / safety-related / delayed switching</li> </ul>		2 4 0
<b>Number of outputs / as contact-less semiconductor switching element</b> <ul style="list-style-type: none"> <li>• safety-related <ul style="list-style-type: none"> <li>• delayed switching</li> <li>• non-delayed</li> </ul> </li> <li>• for reporting function <ul style="list-style-type: none"> <li>• delayed switching</li> <li>• non-delayed</li> </ul> </li> </ul>		0 0 0 0
<b>Stop category / according to DIN EN 60204-1</b>		0

#### General technical details:

<b>Design of the input</b>		
• cascading-input/functional switching		Yes
• feedback input		Yes
• start input		Yes
<b>Design of the electrical connection / jumper socket</b>		Yes
<b>Operating cycles / maximum</b>	1/h	2,000
<b>Switching capacity current</b>		
• of NO contacts of relay outputs		
• at DC-13		
• at 24 V	A	4
• at 115 V	A	0.2
• at 230 V	A	0.1
• at AC-15		
• at 24 V	A	4
• at 115 V	A	4
• at 230 V	A	4
• of NC contacts of relay outputs		
• at DC-13		
• at 24 V	A	1
• at 115 V	A	0.2
• at 230 V	A	0.1
• at AC-15		
• at 24 V	A	4
• at 115 V	A	3
• at 230 V	A	3
<b>Thermal current / of the contact-affected switching element / maximum</b>	A	5
<b>Electrical operating cycles as operating time / typical</b>		100,000
<b>Mechanical operating cycles as operating time / typical</b>		10,000,000
<b>Design of the fuse link / for short-circuit protection of the NO contacts of the relay outputs / required</b>		gL/gG: 4 A, or quick: 6 A
<b>Resistance to direct current / of the cable / maximum</b>	Ω	1,000
<b>Cable length / between sensor and electronic evaluation device / with Cu 1.5 mm<sup>2</sup> and 150 nF/km / maximum</b>	m	2,000
<b>Make time / with automatic start</b>		
• typical	ms	50
• for DC / maximum	ms	100
• for AC / maximum	ms	100
<b>Make time / with automatic start / after mains power cut</b>		
• typical	ms	8,000
• maximum	ms	8,200

<b>Make time / with monitored start</b>		
• maximum	ms	100
• typical	ms	50
<b>Backslide delay time / after opening of the safety circuits / typical</b>	ms	50
<b>Backslide delay time / at mains power cut</b>		
• typical	ms	75
• maximum	ms	125
<b>Recovery time / after opening of the safety circuits / typical</b>	ms	250
<b>Recovery time / after mains power cut / typical</b>	s	8.2
<b>Pulse duration</b>		
• of the sensor input / minimum	ms	30
• of the ON pushbutton input / minimum	s	0.2
• of the cascading-entrance / minimum	s	0.2

#### Control circuit:

<b>Type of voltage / of the controlled supply voltage</b>		AC/DC
<b>Control supply voltage frequency</b>		
• 1 / rated value	Hz	50
• 2 / rated value	Hz	60
<b>Control supply voltage / 1</b>		
• for DC	V	24 ... 240
<b>Control supply voltage / 1 / at 50 Hz</b>		
• for AC	V	24 ... 240
<b>Control supply voltage / 1 / at 60 Hz</b>		
• for AC	V	24 ... 240
<b>operating range factor control supply voltage rated value / of the magnet coil</b>		
• at 50 Hz		
• for AC		0.9 ... 1.1
• at 60 Hz		
• for AC		0.9 ... 1.1
• for DC		0.9 ... 1.1

#### Installation/mounting/dimensions:

<b>mounting position</b>		any
<b>Type of mounting</b>		screw and snap-on mounting
<b>Width</b>	mm	45
<b>Height</b>	mm	138.5
<b>Depth</b>	mm	120

#### Connections:

<b>Design of the electrical connection</b>		screw-type terminals
<b>Type of the connectable conductor cross-section</b>		
<ul style="list-style-type: none"> <li>• solid</li> </ul>		1x (0.5 ... 4 mm <sup>2</sup> ), 2x (0.5 ... 2.5 mm <sup>2</sup> )
<ul style="list-style-type: none"> <li>• finely stranded <ul style="list-style-type: none"> <li>• with wire end processing</li> </ul> </li> </ul>		1x (0.5 ... 2.5 mm <sup>2</sup> ), 2x (0.5 ... 1.5 mm <sup>2</sup> )
<b>Type of the connectable conductor cross-section / for AWG conductors</b>		
<ul style="list-style-type: none"> <li>• solid</li> </ul>		2x (20 ... 14)
<ul style="list-style-type: none"> <li>• stranded</li> </ul>		2x (20 ... 14)

### Product Function:

#### Product function

<ul style="list-style-type: none"> <li>• light barrier monitoring</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• standstill monitoring</li> </ul>	No
<ul style="list-style-type: none"> <li>• protective door monitoring</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• automatic start</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• magnetic switch monitoring Normally closed contact-Normally open contact</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• rotation speed monitoring</li> </ul>	No
<ul style="list-style-type: none"> <li>• laser scanner monitoring</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• monitored start-up</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• light grid monitoring</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• magnetic switch monitoring Normally closed contact-Normally closed contact</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• emergency stop function</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• step mat monitoring</li> </ul>	Yes

#### Suitability for interaction / pressing control

No

#### Acceptability for application

<ul style="list-style-type: none"> <li>• monitoring of floating sensors</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• monitoring of non-floating sensors</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• safety cut-out switch</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• position switch monitoring</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• EMERGENCY-OFF circuit monitoring</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• valve monitoring</li> </ul>	No
<ul style="list-style-type: none"> <li>• tactile sensor monitoring</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• magnetically operated switches monitoring</li> </ul>	Yes
<ul style="list-style-type: none"> <li>• safety-related circuits</li> </ul>	Yes

### Certificates/approvals:

#### Verification of suitability

<ul style="list-style-type: none"> <li>• TÜV (German technical inspectorate) certificate</li> </ul>	UL, CSA, EN 60204-1, EN ISO 12100, EN 954-1, IEC 61508
	Yes

- UL-registration
- BG BIA certificate

Yes  
Yes

**General Product Approval**

**EMC**

**Functional Safety /  
Safety of Machinery**



**Declaration of  
Conformity**

**Test Certificates**

**other**



[Special Test  
Certificate](#)

[Environmental  
Confirmations](#)

**Further information:**

**Information- and Downloadcenter (Catalogs, Brochures,...)**

<http://www.siemens.com/industrial-controls/catalogs>

**Industry Mall (Online ordering system)**

<http://www.siemens.com/industrial-controls/mall>

**Cax online generator:**

<http://www.siemens.com/cax>

**Service&Support (Manuals, Certificates, Characteristics, FAQs,...)**

<http://support.automation.siemens.com/WWW/view/en/3TK2826-1CW30/all>

**Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)**

[http://www.automation.siemens.com/bilddb/cax\\_en.aspx?mlfb=3TK2826-1CW30](http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3TK2826-1CW30)

**last change:**

Feb 18, 2013