

REMOTE CONTROL F. MOTOR SZ S2. AC 230V,
50HZ

General technical data:		
product brand name		SIRIUS
Product designation		Motor remote operating mechanism
Size of the circuit-breaker		S2
Design of the product		standard
Control version of the switch operating mechanism		Motor
Suitability for use		circuit-breakers S2
Ambient temperature		
• during storage	°C	-50 ... +80
• during operation	°C	-20 ... +70
Shock resistance		25g / 11 ms
Operating frequency maximum	1/h	25
Color of the actuating element		black



Control circuit/ Control:		
Type of voltage of the control supply voltage		AC
Control supply voltage frequency		
• 1		
— Initial rated value	Hz	50
— Final rated value	Hz	60
Control supply voltage		
• 1		
— at AC		
— at 50 Hz rated value	V	230
— at 50 Hz Initial rated value	V	195.5
— at 50 Hz Final rated value	V	253
— at 60 Hz rated value	V	230
— at 60 Hz Final rated value	V	253
— at 60 Hz Initial rated value	V	195.5

Installation/ mounting/ dimensions:		
Mounting position		any
Mounting type		screw fixing
Width	mm	148
Height	mm	224
Depth	mm	211
Required spacing for grounded parts		

- forwards
- Backwards
- upwards
- at the side
- downwards

mm	0
mm	0
mm	0
mm	0
mm	0

Certificates/ approvals:

Certificate of suitability		CE	
Declaration of Conformity	Test Certificates	Shipping Approval	other
 EG-Konf.	spezielle Prüfbescheinigung <u>n</u>	 BUREAU VERITAS	 RMRS
			Umweltbestätigung Bestätigungen

other



Further information

- Information- and Downloadcenter (Catalogs, Brochures,...)**
<http://www.siemens.com/industrial-controls/catalogs>
- Industry Mall (Online ordering system)**
<http://www.siemens.com/industrymall>
- Cax online generator**
<http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RV1936-3AP0>
- Service&Support (Manuals, Certificates, Characteristics, FAQs,...)**
<https://support.industry.siemens.com/cs/ww/en/ps/3RV1936-3AP0>
- Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)**
http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RV1936-3AP0&lang=en

last modified: 10/07/2016