

**018F7351****Solenoid coil, BB230AS, DIN Spade, Supply voltage [V] AC: 230, Multi pack**

Electrical connection: DIN Spade, Supply voltage [V] AC: 230, Frequency [Hz]: 50 Hz, Enclosure rating IP: IP00

**PRODUCT DETAILS**

<b>Gross weight</b>	0.274 Kilogram
<b>Net weight</b>	0.252 Kilogram
<b>Volume</b>	0.266 Liter
<b>EAN</b>	5702428026475
<b>Actuator size</b>	13.5 mm
<b>Ambient temperature range [°C] [max]</b>	80 °C
<b>Ambient temperature range [°C] [min]</b>	-40 °C
<b>Ambient temperature range [°F] [max]</b>	176 °F
<b>Ambient temperature range [°F] [min]</b>	-40 °F
<b>Approval</b>	CE EAC LLC CDC TYSK UKCA
<b>CE evaluated</b>	Yes
<b>China RoHS compliance</b>	Out of scope
<b>Coil connection</b>	DIN Spade
<b>Coil design standard</b>	VDE 0580
<b>Coil fastening</b>	Clip-on
<b>Coil winding insulation class</b>	Class H to IEC 85
<b>Colour</b>	Blue
<b>Compliance</b>	EN 60730-1
<b>Contain batteries</b>	No
<b>Duty rating</b>	Continuous
<b>EEE category</b>	5 small equipment (any external dimension < 50 cm)
<b>Electrical connection</b>	DIN Spade
<b>Electrical connection size</b>	6.3 mm x 0.8 mm
<b>Electrical connection standard</b>	EN175301-803
<b>Electrical connector</b>	3 x spades
<b>Enclosure rating IP</b>	IP00
<b>EPD available</b>	Yes
<b>EU RoHS compliance</b>	Out of scope
<b>Frequency [Hz]</b>	50 Hz
<b>Identical product</b>	018F8351
<b>In scope of WEEE</b>	Yes

Danfoss can accept no responsibility for possible errors in catalogs, brochures and other printed material. Danfoss reserves the right to alter its products without notice. This also applies to products already on order provided that such alterations can be made without sub-sequential changes being necessary in specifications already agreed. All trademarks in this material are property of the respective companies. Danfoss and the Danfoss logotype are trademarks of Danfoss A/S. All rights reserved.

**Product Detail | Solenoid coil, BB230AS, DIN Spade, Supply voltage [V] AC: 230, Multi pack**
**PRODUCT DETAILS**

<b>Manufacturer's name</b>	Danfoss
<b>Packing format</b>	Multi pack
<b>Parts Program name</b>	EV210B EV212B EV220B 15 - 50 EV220B 6 - 22 EV220B 65 - 100 EV222B EV224B EV250B EV251B EV310B
<b>Power consumption 50Hz [VA]</b>	19 VA
<b>Power consumption [W] 50Hz</b>	11 W
<b>Product accessories</b>	Solenoid coil accessories
<b>Product group</b>	Solenoid valves
<b>Product Name Description</b>	Solenoid coil
<b>Quantity per packing format</b>	50 pc
<b>REACH Candidate List substances</b>	No
<b>Rel. Humidity [% RH] [max]</b>	97 %
<b>Rel. Humidity [% RH] [min]</b>	0 %
<b>Rel. Humidity conditions</b>	Non-condensation
<b>SCIP dossier product name</b>	Solenoid coils
<b>Serviceable</b>	No
<b>Spare part number</b>	018F7351
<b>Supply voltage 50Hz Max [V]</b>	230 V
<b>Supply voltage [V] AC</b>	230 V
<b>Type</b>	BB230AS
<b>Type designation</b>	BB230AS

**For Documents, Software, Visuals and more information, please use this link to visit the product page on Danfoss Product Store [🔗](#)**

**Accessories**


**042N0185 [🔗](#)**



**042N0263 [🔗](#)**

**Spare part, 042N Coil Type B; 018F Coil Type B; 018Z Coil Type B, Cable plug**

Product Type: Spare part, Used for product: 042N Coil Type B; 018F Coil Type B; 018Z Coil Type B,

Type designation: Cable plug, Cable plug

**For more information, please use this link to visit the product page on Danfoss Product Store [🔗](#)**

Danfoss can accept no responsibility for possible errors in catalogs, brochures and other printed material. Danfoss reserves the right to alter its products without notice. This also applies to products already on order provided that such alterations can be made without sub-sequential changes being necessary in specifications already agreed. All trademarks in this material are property of the respective companies. Danfoss and the Danfoss logotype are trademarks of Danfoss A/S. All rights reserved.

**Accessories**

---

**042N0265** [🔗](#)**Spare part, 042N Coil Type B; 018F Coil Type B; 018Z Coil Type B, Cable plug**

Product Type: Spare part, Used for product: 042N Coil Type B; 018F Coil Type B; 018Z Coil Type B,  
Type designation: Cable plug, Cable plug

---

**042N1256** [🔗](#)**Spare part, 042N Coil Type B; 018F Coil Type B; 018Z Coil Type B, Cable plug**

Product Type: Spare part, Used for product: 042N Coil Type B; 018F Coil Type B; 018Z Coil Type B,  
Type designation: Cable plug, Cable plug

---

**042N1278** [🔗](#)**Spare part, 042N Coil Type B; 018F Coil Type B; 018Z Coil Type B, Cable plug**

Product Type: Spare part, Used for product: 042N Coil Type B; 018F Coil Type B; 018Z Coil Type B,  
Type designation: Cable plug, Cable plug

---

**For more information, please use this link to visit the product page on Danfoss Product Store** [🔗](#)

Danfoss can accept no responsibility for possible errors in catalogs, brochures and other printed material. Danfoss reserves the right to alter its products without notice. This also applies to products already on order provided that such alterations can be made without sub-sequential changes being necessary in specifications already agreed. All trademarks in this material are property of the respective companies. Danfoss and the Danfoss logotype are trademarks of Danfoss A/S. All rights reserved.