

UPS-BAT-KIT/PB/2X12V/1.2AH - Uninterruptible power supply replacement battery



1283114

<https://www.phoenixcontact.com/gb/products/1283114>

Please be informed that the data shown in this PDF document is generated from our online catalog. Please find the complete data in the user documentation. Our general terms of use for downloads are valid.



Replacement battery, VRLA-AGM, 2x12 V DC, 1.2 Ah. Only for 1274520 UPS-BAT/PB/24DC/1.2AH and 2320254 QUINT-UPS/24DC/24DC/5/1.3AH from V/C 05

Commercial data

| | |
|--------------------------------------|---------------|
| Item number | 1283114 |
| Packing unit | 1 pc |
| Minimum order quantity | 1 pc |
| Sales key | CMUEV3 |
| Product key | CMUEV3 |
| GTIN | 4063151482398 |
| Weight per piece (including packing) | 1,264 g |
| Weight per piece (excluding packing) | 1,264 g |
| Customs tariff number | 85072080 |
| Country of origin | CN |

UPS-BAT-KIT/PB/2X12V/1.2AH - Uninterruptible power supply replacement battery



1283114

<https://www.phoenixcontact.com/gb/products/1283114>

Technical data

Notes

General

| | |
|---------------------|---|
| Note on the battery | This product contains a battery with a limited shelf life that must be charged every few months. The product packaging indicates when the battery must be started up or recharged. The general shelf life can be found in the energy storage devices area under "Latest startup". |
|---------------------|---|

Energy storage

Input

| | |
|------------------|---------|
| Input voltage | 2x 12 V |
| Nominal capacity | 1.2 Ah |

General

| | |
|--|---|
| Battery type | BB Battery BP1.2-12FR |
| Battery technology | VRLA-AGM |
| IQ-Technology | no |
| Latest startup date (battery only) | 3 Months (0 °C ... 20 °C) 1 Months (30 °C ... 40 °C) |
| Latest startup (battery only) - range | 1 Months ... 3 Months (20 °C ... 30 °C) |
| Accumulator module service life (according to Eurobat) | 6 (20 °C) |

Product properties

| | |
|----------------|---|
| Product type | Battery |
| Product family | Replacement battery |
| Disposal | Used batteries must not be thrown away with household waste, they should instead be disposed of in accordance with applicable national regulations. |

Insulation characteristics

| | |
|---------------------|-----|
| Protection class | III |
| Degree of pollution | 2 |

Dimensions

Item dimensions

| | |
|--------|--------|
| Width | 47 mm |
| Height | 117 mm |
| Depth | 99 mm |

Environmental and real-life conditions

Ambient conditions

UPS-BAT-KIT/PB/2X12V/1.2AH - Uninterruptible power supply replacement battery



1283114

<https://www.phoenixcontact.com/gb/products/1283114>

| | |
|--|------------------|
| Degree of protection | IP20 |
| Ambient temperature (storage/transport) | -20 °C ... 40 °C |
| Ambient temperature (charge) | 0 °C ... 40 °C |
| Ambient temperature (discharge) | -20 °C ... 50 °C |
| Max. permissible relative humidity (operation) | ≤ 95 % |

Ex data

| | |
|----------------------------|----|
| Suited for EX-applications | no |
|----------------------------|----|

UPS-BAT-KIT/PB/2X12V/1.2AH - Uninterruptible power supply replacement battery



1283114

<https://www.phoenixcontact.com/gb/products/1283114>

Approvals

To download certificates, visit the product detail page: <https://www.phoenixcontact.com/gb/products/1283114>



GOST-R

Approval ID: ROSS DE.BL08.D00191



EAC

Approval ID: RU*DE*01.B.78948/21

UPS-BAT-KIT/PB/2X12V/1.2AH - Uninterruptible power supply replacement battery



1283114

<https://www.phoenixcontact.com/gb/products/1283114>

Classifications

ECLASS

| | |
|-------------|----------|
| ECLASS-13.0 | 27059090 |
| ECLASS-15.0 | 27059090 |

ETIM

| | |
|----------|----------|
| ETIM 9.0 | EC002839 |
|----------|----------|

UNSPSC

| | |
|-------------|----------|
| UNSPSC 21.0 | 26111700 |
|-------------|----------|

UPS-BAT-KIT/PB/2X12V/1.2AH - Uninterruptible power supply replacement battery



1283114

<https://www.phoenixcontact.com/gb/products/1283114>

Environmental product compliance

EU RoHS

| | |
|---|---|
| Fulfills EU RoHS substance requirements | Not applicable, No electrical and electronic equipment (EEE), cannot be used in EEE |
|---|---|

China RoHS

| | |
|--|---|
| Environment friendly use period (EFUP) | EFUP-8 An article-related China RoHS declaration table can be found in the download area for the respective article under "Manufacturer declaration". For all articles with EFUP-E, no China RoHS declaration table issued and required. |
|--|---|

EU REACH SVHC

| | |
|-------------------------------------|--------------------------------------|
| REACH candidate substance (CAS No.) | Lead(CAS: 7439-92-1) |
| SCIP | 0f0d2487-3dac-48f8-a976-fa2eee85acb8 |

Phoenix Contact 2025 © - all rights reserved
<https://www.phoenixcontact.com>

PHOENIX CONTACT Ltd
Halesfield 13, Telford
Shropshire, TF7 4PG
01952 681700
info@phoenixcontact.co.uk