


Product datasheet

Specifications



Set of 2 lifting eyes M8. Maximum load: 210kg

Local distributor code:
392863489

NSYAELYTCRG8

EAN Code: 3606480168727

Main

Area	PanelSeT
category	Lifting accessory
Product or component type	Lifting eye
Application	Multi-purpose
Mounting location	Enclosure top
Range compatibility	PanelSeT PanelSeT CRN PanelSeT PanelSeT S3D
Device composition	2 eyebolt 2 bracket 2 washer 2 nut fixing elements
Quantity per set	Set of 1

Complementary

Material	Eyebolt: moulded steel Bracket: galvanised steel
Surface finish	Zinc coated
Fixing mode	Screwed
Permanent permissible load	200 kg slinging at 60°
Height	55 mm
Width	120 mm
Depth	30 mm
Diameter	29 mm
ISO thread	M8
Net weight	0.24 kg

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	4.000 cm
Package 1 Width	9.000 cm
Package 1 Length	12.000 cm
Package 1 Weight	268.000 g

Unit Type of Package 2	CAR
Number of Units in Package 2	40
Package 2 Height	21.000 cm
Package 2 Width	40.500 cm
Package 2 Length	30.000 cm
Package 2 Weight	10.742 kg
Unit Type of Package 3	P12
Number of Units in Package 3	640
Package 3 Height	56.000 cm
Package 3 Width	80.000 cm
Package 3 Length	120.000 cm
Package 3 Weight	182.000 kg

Logistical informations

Country of origin	FR
--------------------------	----

Contractual warranty

Warranty (in months)	18
-----------------------------	----

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint

[Environmental Disclosure](#)

[Product Environmental Profile](#)

Use Better

Materials and Substances

Packaging made with recycled cardboard

No

Packaging without single use plastic

No

[EU RoHS Directive](#)

Pro-active compliance (Product out of EU RoHS legal scope)

REACH Regulation

[REACH Declaration](#)

Use Again

Repack and remanufacture

End of life manual availability

No need of specific recycling operations

Take-back

No