

SINAMICS BRAKING RESISTOR INPUT: 1035 V DC OUTPUT: 125 KW/15 S 9,8 OHM



Figure similar

Order number	
Phase number / of the input voltage	Wert fehlt!
Type of voltage / of the input voltage	Wert fehlt!
Input voltage	Wert fehlt! ... Wert fehlt!
DC link voltage	890 ... 1 035
Consumed active power / rated value	25 kW
• maximum	125 kW
Type of electrical connection / for power cable	M10 screw studs
Connectable conductor cross-section / for power cable	50 mm <sup>2</sup>
Input voltage / of the temperature switch / at AC / maximum	Wert fehlt!
Protection class IP	IP20
Electrical resistance / of the braking resistor	9.8 Ω
Width	740 mm
Height	600 mm
Depth	486 mm
Net weight	50 kg

## Further information

### **Information und Download Center**

[https://www.automation.siemens.com/mcms/infocenter/content/en/Pages/order\\_form.aspx](https://www.automation.siemens.com/mcms/infocenter/content/en/Pages/order_form.aspx)

### **Technical documentation**

<http://w3.siemens.com/mcms/mc-solutions/en/motion-control/support/technical-documentation/Pages/technical-documentation.aspx>

### **Industry Mall**

<https://eb.automation.siemens.com/mall/en/WW/Catag/Product/6SL3000-1BH31-3AA0/all>

### **Industry Online Support**

<http://support.automation.siemens.com/WW/view/en/6SL3000-1BH31-3AA0/all>