

Product datasheet

Specifications



Microswitches OF/SDE/PF and wiring - for Masterpact MTZ1

LV847906

EAN Code: 3606480809620

Main

Range	MasterPact
Device short name	OF PF micro switch SDE
Product or component type	Auxiliary contact block
Device application	Control
Range compatibility	MasterPact MTZ1 circuit breaker

Complementary

Auxiliary contacts type	Standard
Signal contacts composition	4 NO/NC
Breaking capacity	6 A AC-12 240/380 V AC 50/60 Hz 0.5 A DC-12 125 V DC 6 A AC-12 480 V AC 50/60 Hz 6 A AC-12 690 V AC 50/60 Hz 2.5 A DC-12 24/48 V DC 0.3 A DC-12 250 V DC
Minimum load	100 mA at 24 V

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	3.500 cm
Package 1 Width	6.500 cm
Package 1 Length	10.000 cm
Package 1 Weight	18.000 g
Unit Type of Package 2	BB1
Number of Units in Package 2	20
Package 2 Height	9.000 cm
Package 2 Width	19.500 cm
Package 2 Length	29.800 cm
Package 2 Weight	498.000 g
Unit Type of Package 3	S03
Number of Units in Package 3	80

Package 3 Height	30.000 cm
Package 3 Width	30.000 cm
Package 3 Length	40.000 cm
Package 3 Weight	2.467 kg

Logistical informations

Country of origin TH

Contractual warranty

Warranty (in months) 18


Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.



[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

 Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	Yes
EU RoHS Directive	Compliant with Exemptions
REACH Regulation	REACH Declaration
Halogen-free status	Product contains halogen above thresholds

Use Again

 Repack and remanufacture	
Take-back	No
WEEE Label	 The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins