

SITOR fuse holder 22x 127 63 A 1500 V AC/1000 V DC 2-pole



Model	
Product designation	SITOR fuse switch disconnecter
Design of the operating mechanism	Cover handle
General technical data	
Number of poles	2
Size of fuse link	Other
Usage category	AC20B/DC20B
Size of the fuse link	22x127 mm
Protection class	
Protection class IP / on the front	IP20
Electricity	
Continuous current / rated value	63 A
Main circuit	
Operating voltage	
<ul style="list-style-type: none"> <li>at AC / rated value / maximum</li> <li>at DC / rated value / maximum</li> </ul>	<p>1 500 V</p> <p>1 000 V</p>
Suitability	

<b>Suitability for use</b>	
• Main switch	No
• switch disconnecter	No
• EMERGENCY OFF switch	No
• safety switch	No

<b>Product function</b>	
Product function / fuse monitoring	No

<b>Short circuit</b>	
Conditional short-circuit current (I <sub>q</sub> ) / rated value	50 kA

<b>Connections</b>	
Connectable conductor cross-section / stranded	
• minimum	1 mm <sup>2</sup>
• maximum	50 mm <sup>2</sup>
Connectable conductor cross-section / solid	
• minimum	1 mm <sup>2</sup>
• maximum	50 mm <sup>2</sup>
Type of electrical connection / for main current circuit	screw-type terminals

<b>Mechanical Design</b>	
Height	200 mm
Depth	102 mm
Mounting type	
• floor mounting	Yes
• front mounting	No
• rail mounting	No
Net weight	960 g

### General Product Approval

[Miscellaneous](#)

### Further information

#### Information- and Downloadcenter (Catalogs, Brochures,...)

<http://www.siemens.com/lowvoltage/catalogs>

#### Industry Mall (Online ordering system)

<https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3NC2392-0MK>

#### Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

<https://support.industry.siemens.com/cs/ww/en/ps/3NC2392-0MK>

#### Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)

[http://www.automation.siemens.com/bilddb/cax\\_en.aspx?mlfb=3NC2392-0MK](http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3NC2392-0MK)

#### CAX-Online-Generator

<http://www.siemens.com/cax>

