



INPUT INTERFACE WITH PLUG-IN REL. 1 CH. CON.  
HARD GOLD-PLAT. SCREW TERMINAL 24 V DC  
ENCLOSURE WIDTH 6.2 MM

General technical details:		
Type of voltage		DC
Control supply voltage		
<ul style="list-style-type: none"> <li>for DC / rated value</li> </ul>		
<ul style="list-style-type: none"> <li>minimum</li> </ul>	V	24
<ul style="list-style-type: none"> <li>maximum</li> </ul>	V	24
Switching behaviour		monostable
Number of NC contacts / for auxiliary contacts		0
Number of NO contacts / for auxiliary contacts		0
Number of changeover contacts / for auxiliary contacts		1
Operating current / of the auxiliary contacts		
<ul style="list-style-type: none"> <li>at DC-13</li> </ul>		
<ul style="list-style-type: none"> <li>at 24 V</li> </ul>	A	1
<ul style="list-style-type: none"> <li>at 110 V</li> </ul>	A	0.2
<ul style="list-style-type: none"> <li>at 230 V</li> </ul>	A	0.1
<ul style="list-style-type: none"> <li>at AC-15</li> </ul>		
<ul style="list-style-type: none"> <li>at 230 V</li> </ul>	A	3
Reference code / according to DIN 40719 extended according to IEC 204-2 / according to IEC 750		K
Reference code / according to DIN EN 61346-2		K




### Mechanical design:

Design of the electrical connection		screw-type terminals
Design of the electrical connection / jumper socket		Yes
Design of the relay operating mechanism		poled
Design of the switching function		changeover switch
• guided		No
Product component / jumper socket		Yes
Width	mm	6.2
Height	mm	89.5
Depth	mm	92

### Ambient conditions:

Protection class IP		IP20
Ambient temperature		
• during operating	°C	-25 ... +55

### Certificates/approvals:

General Product Approval	Test Certificates	other
 CCC		 UL
	<a href="#">Special Test Certificate</a>	<a href="#">Declaration of Conformity</a>

### Further information:

#### Information- and Downloadcenter (Catalogs, Brochures,...)

<http://www.siemens.com/industrial-controls/catalogs>

#### Industry Mall (Online ordering system)

<http://www.siemens.com/industrial-controls/mall>

#### CAX-Online-Generator

<http://www.siemens.com/cax>

#### Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

<http://support.automation.siemens.com/WW/view/en/3TX7014-1BM02/all>

#### Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)

[http://www.automation.siemens.com/bilddb/cax\\_en.aspx?mlfb=3TX7014-1BM02](http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3TX7014-1BM02)

last change:

Jun 16, 2014