

## PSEN ml / PSENcs Y junction M12

570489



Y-junction for integration of PSENcode into a PSENmlock series connection, IP67, 3 x M12/8pin. SDD Setting: Please use PSEN Y junction M12 cable channel or PSEN Y junction M12 SENSOR.

### Technical details

|                                   |             |
|-----------------------------------|-------------|
| Ambient temperature:              | -20 - 80 °C |
| Degree of protection connector 1: | IP67        |
| Degree of protection connector 2: | IP67        |