

TRANSFORMER SITAS;
 PHASES:1;
 PN/PN(S6)(KVA):0,315 /1,12;
 UPRI(V):400-230+/-15;
 USEC(V):230-115;
 ISEC(A):1,37-2,74;
 F(HZ):50...60;
 VECTOR GR./SHIELD WNG.:li0 /0;
 TA/ISOKL:40 /B;
 IP00;
 TYPE OF TERMINALS:SCREW/TAB CONNECTION;
 INSTALLATION:SCREW;
 EN 61558-2-1, -2-2,
 -2-4 >UL/CSA-RECOGNIZED< >CONTROL CIRCUIT
 TRANSFORMER< >ISOLATION TRANSFORMER<

General technical details:

Product designation		transformer SITAS
product brand name		SIDAC
Operating apparent output / rated value	V·A	315
Efficiency		0.9
Manner of switching for transformers		li0
Verification of suitability		CE / cRUus
Product function		
• temperature surveillance		No
• isolation control		No
• short circuit and overload protection		No
Number of the protective coils		0
Short-term vector power	V·A	1,120
Relative short-circuit voltage	%	4.97

Inputs:

Phase number / of the inputs		1
Input voltage		
• _1 / rated value	V	415
• _2 / rated value	V	400
• _3 / rated value	V	385
• _4 / rated value	V	245
• _5 / rated value	V	230
• _6 / rated value	V	215

Electrical input frequency		
• minimum	Hz	50
• maximum	Hz	60

Outputs:

Phase number / of the outputs		1
Output voltage		
• _1 / rated value	V	230
• _2 / rated value	V	115
Electrical output frequency		
• maximum	Hz	60
• minimum	Hz	50




Ambient conditions:

Thermal class / according to IEC 60085		B
Ambient temperature / rated value	°C	40
Protection class IP		IP00

Mechanical design:

Design of the electrical connection		
• secondary side / for main current circuit		screw-type terminals / tab terminals
• at the input / for main current circuit		screw-type terminals / tab terminals
Mounting type		screws
Construction form of the iron core		EI 105/60
Width	m	0.107
Height	m	0.111
Depth	m	0.12

Certificates/approvals:

General Product Approval	Shipping Approval	other
	 GOST	 PRS
		other

Further information:

Information- and Downloadcenter (Catalogs, Brochures,...) http://www.siemens.com/industrial-controls/catalogs
Industry Mall (Online ordering system) http://www.siemens.com/industrial-controls/mall
CAX-Online-Generator http://www.siemens.com/cax
Service&Support (Manuals, Certificates, Characteristics, FAQs,...) http://support.automation.siemens.com/WW/view/en/4AM4342-8JD40-0FA0/all

last change:

Dec 5, 2011