



WINDOW-TYPE CURRENT TRANSFORMER,  
CLASS 1 150A/1A,  
2,5VA PRIMARY CURRENT 150A, 2.5VA

Similar to image

**General technical details:**

<b>product designation</b>		window-type current transformers
<b>Accuracy class / of the current transformer</b>		class 1
<b>Ratio input current/output current</b>		150/1 A
<b>Current</b>		
• at the input / rated value	A	150
• secondary side / rated value	A	1
<b>Operating apparent output / rated value</b>	V·A	2.5
<b>Ambient temperature</b>		
• during operating	°C	-10 ... +55
<b>Item designation</b>		
• according to DIN 40719 extendable after IEC 204-2 / according to IEC 750		T
• according to DIN EN 61346-2		T

**Mechanical design:**

<b>Width / of the push-through bus bar</b>		
• in case of 1 bus bar / maximum	mm	12
<b>Outer diameter / of the push-through conductor / maximum</b>	mm	17.5
<b>Protection class IP</b>		IP20

<b>Depth</b>	mm	80
<b>Height</b>	mm	74.5
<b>Width</b>	mm	48
<b>Type of mounting</b>		screw fixing
<b>Design of the electrical connection / secondary side</b>		screw-type terminals
<b>Product equipment / touch-protection</b>		Yes

#### Certificates/approvals:

General Product Approval

Declaration of Conformity



GOST



EG-Konf.

#### Further information:

##### Information- and Downloadcenter (Catalogs, Brochures,...)

<http://www.siemens.com/lowvoltage/catalogs>

##### Industry Mall (Online ordering system)

<http://www.siemens.com/lowvoltage/mall>

##### Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

<http://support.automation.siemens.com/WW/view/en/4NC5121-0CC20/all>

##### Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)

[http://www.automation.siemens.com/bilddb/cax\\_en.aspx?mlfb=4NC5121-0CC20](http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=4NC5121-0CC20)

##### CAX-Online-Generator

<http://www.siemens.com/cax>

##### Tender specifications

[Datanorm](#) [GAEB81](#) [GAEB83](#) [RTF](#) [TXT](#)

last change:

Dec 17, 2012