

## WKB 2/3

Weidmüller Interface GmbH &amp; Co. KG

Klingenbergstraße 26

D-32758 Detmold

Germany

www.weidmueller.com

## Product image

**Current and voltage transformer wiring**

Our test disconnect terminal blocks featuring spring and screw connection technology allow you to create all the important converter circuits for measuring current, voltage and power in a safe and sophisticated way.

**General ordering data**

Version	Accessories, Cross-connection slider
Order No.	<a href="#">1936200000</a>
Type	WKB 2/3
GTIN (EAN)	4032248605934
Qty.	50 pc(s).

Creation date March 26, 2021 10:15:47 AM CET

Catalogue status 12.03.2021 / We reserve the right to make technical changes.

## WKB 2/3

Weidmüller Interface GmbH &amp; Co. KG

Klingenbergstraße 26

D-32758 Detmold

Germany

www.weidmueller.com

## Technical data

## Dimensions and weights

Depth	16.1 mm	Depth (inches)	0.634 inch
Height	9.41 mm	Height (inches)	0.37 inch
Net weight	2.9 g	Width	22 mm
Width (inches)	0.866 inch		

## Temperatures

Continuous operating temp., min.	-50 °C	Continuous operating temp., max.	100 °C
----------------------------------	--------	----------------------------------	--------

## Material data

Material	Polyamide 66	Colour	orange
UL 94 flammability rating	V-2		

## System specifications

Version	Cross-connector accessories
---------	-----------------------------

## Additional technical data

Installation advice	Direct mounting	Type of fixing	Plugged
Type of mounting	Clamped		

## Dimensions

Pitch in mm (P)	7.9 mm	TS 35 offset	45.5 mm
-----------------	--------	--------------	---------

## General

Installation advice	Direct mounting	Number of poles	3
Operating temperature range, max.	100 °C		

## Classifications

ETIM 6.0	EC000489	ETIM 7.0	EC000489
ECLASS 9.0	27-14-11-40	ECLASS 9.1	27-14-11-40
ECLASS 10.0	27-14-11-40	ECLASS 11.0	27-14-11-40

## Approvals

ROHS	Conform
------	---------

## Downloads

Engineering Data	<a href="#">STEP</a>
Engineering Data	<a href="#">EPLAN, WSCAD, Zuken E3.S</a>
User Documentation	<a href="#">StorageConditionsTerminalBlocks</a>